



POW-R-STOCK^{Plus} PANEL SELECTION

INTERIOR

VOLTAGE	PHASE	AMPS	CIRCUITS	BUS
120/240 = 1A	1P3W = 1	100	18	Aluminum = A Copper = C
208/120 = 1A	3P4W = 3	100	30	
480/277 = 2A	3P4W = 3	225	30	
		225	42	
		400	42	

PRL ___ X ___ (S)*

* S = SHORT. Add the "S" suffix for 225 Amp 42 circuit configurations that are TOP-FEED ONLY and do not include through-feed lugs or a sub-feed breaker. The SHORT interiors use the 48 inch box (EZB2048RBS) and trim (EZT2048S). Bid Manager will default to the SHORT interior when applicable. To use the standard 42 circuit interior, change the 'Box Height' to 60 on the 'Layout' tab.

BOX

18 Circuits	30 Circuits	42 Circuits (225 AMP)	42 Circuits (400 AMP)	3R Enclosures
EZB2036RBS	EZB2048RBS	EZB2060RBS	EZB2072RBS	GWPBQ2048PR - 48" GWPBQ2060PR - 60" GWPBQ2072PR - 72"

TRIM

18 Circuits	30 Circuits	42 Circuits (225 AMP)	42 Circuits (400 AMP)
EZT2036S	EZT2048S	EZT2060S	EZT2072S



POW-R-STOCK^{Plus} BREAKER SELECTION

MAIN DEVICE

MAIN BREAKER

	100 - 225 Amp	250 - 400 Amp
PRL1A	ED *	KD**
PRL2A	FD	KD

* Bid Manager defaults to the EDB or BAB-H Frame. Change it to ED for Pow-R-Stock.

** Bid Manager defaults to DK Frame. Change it to KD for Pow-R-Stock.

BK **T or B**
 _____ _____
FRAME **AMP RATING** **INCOMING***
 * T = Top / B = Bottom

MAIN LUGS ONLY (MLO)

100 Amp	225 Amp *	400 Amp
LUGKIT100	LUGKIT225 **	LUGKIT400

* MLO SHORT interiors available for 225 Amp 42 circuit configurations are:

120/208 = PRL1A3225L42AS (AL) or CS (CU)

480/277 = PRL2A3225L42AS (AL) or CS (CU)

EZB2042R (Box) and EZT2042S (Trim)

** To accommodate Through-Feed Lugs, use:

120/208 = PRL1A3225X42A (AL) or C (CU)

480/277 = PRL2A3225X42A (AL) or C (CU)

EZB2060R (Box) and EZT2060S (Trim)

BREAKERS

BRANCH BREAKERS

	PRL1A			PRL2A
KAIC	10KA	10KA (GFCI)	22KA	14KA
FRAME	BAB	QBGF	QBHW	GHB
POLES / AMPS	1P 15-60A 2P 15-100A 3P 15-100A *	1P 15-30A 2P 15-40A	1P 15-60A 2P 15-100A 3P 15-100A	1P 15-100A 2P 15-100A 3P 15-100A

* The BAB 3-pole breaker part numbers end in an "H". (example BAB3015H)

_____ _____ _____
FRAME **POLES** **AMP RATING**

SUB-FEED BREAKER OPTIONS *

	PRL1A	PRL2A
	BKED	BKFD
225 Amp	PRL1A3225X42A (AL) or C (CU) EXB2060R (Box) EXT2060S (Trim)	PRL2A3225X42A (AL) or C (CU) EXB2060R (Box) EXT2060S (Trim)
400 Amp	PRL1A3400X42A (AL) or C (CU) EXB2072R (Box) EXT2072S (Trim)	PRL2A3400X42A (AL) or C (CU) EXB2072R (Box) EXT2072S (Trim)

* To accommodate a sub-feed breaker, refer to the above chart for available panel options.

KITS

OTHER ACCESSORIES

	100 Amp	225 Amp	400 Amp
SERVICE ENTRANCE KIT	SEK1/2	SEK1/2	SEK4/6
200% NEUTRAL KIT	2NK100	2NK225	N/A

ISOLATED GROUND BAR KIT	ISOGROUND
COPPER GROUND BAR KIT	CUGROUND
1P FILLER PLATE	5155C62H01